



**Product Code** PS2001

**Description**

1000W Pure Sine Wave Power Inverter  
Portable power for AC products, AC outlets for connecting multiple loads  
High surge capacity for products that require more power to start  
High efficiency converts virtually all of the battery's power to AC



**Specification**

Continuous Output Power (Watt): 1000  
Output Peak Power (Watt): 2000  
Input Voltage (DC): 12V( 11~15V)  
Output Voltage (AC): 220~240V  
eight(KGS): 2.5Kg  
Output Waveform: Pure sine wave  
Efficiency: 85~90%  
Low Battery Voltage Alarm Alarm (Volt): 10V ±0.5V/21±1V  
Low Battery Voltage shutdown (Volt): 10V ±0.5V/20±1V  
Replaceable Fuse: 30A\*4  
Dimension(L\*W\*H)275\*220\*78mm  
Over temperature shutdown: < 65°C

Cooling Mode: By Fan  
Frequency: 50Hz ±3Hz  
Accessory: 1, Power Cable + Bolts

Mounting brackets for convenient installation  
Overload and over temperature shut down.  
Low voltage and over voltage alarm.  
Low voltage and over voltage cut off.  
Input reverse protection.  
Short circuit protection.

MULTI WAY 240v OUTPUT PLUG (UK/EU/USA)

**Approvals** CE



**Box Contents**

Inverter, Cables, Manual